

2 Way SMA Wilkinson Power Divider From 4 GHz to 8 GHz Rated at 10 Watts



Power Dividers Technical Data Sheet PE2080 Features 2-Way Power Divider Max Power 10 Watts (CW) Wilkinson Design Insertion Loss < 0.35 dB • 4 to 8 GHz Frequency Range Isolation > 20 dB **Applications** Test and Measurement Commercial Communications SATCOM Military Communications Wireless Communications

Description

Pasternack carries a wide selection of power dividers to fit your needs. These components are essential in many systems, allowing the combination of multiple signals or splitting of a single signal into multiple signals with equal magnitude and phase. Pasternack's resistive and Wilkinson power dividers come with excellent performance featuring minimal loss, high isolation and low VSWR. They are available in both narrow and broad bandwidths with a variety of connector types such as 2.92mm, BNC, N and SMA.

The PE2080 is a 2-way Wilkinson power divider that operates from 4 to 8 GHz and can handle up to 10 Watts (CW) with 0.35 dB max insertion loss and 20 dB min isolation. The package interface uses SMA connectors and is REACH and RoHS compliant.

Wilkinson

2

Electrical Specifications

Design

Number of Output Ports

Description	Minimum	Typical	Maximum	Units
Frequency Range	4		8	GHz
Impedance		50		Ohms
Input VSWR			1.3:1	
Output VSWR			1.3:1	
Insertion Loss			0.35	dB
Isolation	20			dB
Input Power (CW)			10	Watts

Electrical Specification Notes:

Max input power rated for load VSWR of 1.25:1 or better.

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: 2 Way SMA Wilkinson Power Divider From 4 GHz to 8 GHz Rated at 10 Watts PE2080

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 Phone: (866) 727-8376 or (949) 261-1920 • Fax: (949) 261-7451

Sales@Pasternack.com • Techsupport@Pasternack.com



2 Way SMA Wilkinson Power Divider From 4 GHz to 8 GHz Rated at 10 Watts

Power Dividers Technical Data Sheet

Mechanical Specifications

Size Length Width Height Weight

Configuration Package Type Input Connector Output Connectors 1 in [25.4 mm] 1 in [25.4 mm] 0.5 in [12.7 mm] 0.082 lbs [37.19 g]

Connectorized SMA Male SMA Female

Compliance Certifications (see product page for current document)

Plotted and Other Data

Notes:

2 Way SMA Wilkinson Power Divider From 4 GHz to 8 GHz Rated at 10 Watts from Pasternack Enterprises has same day shipment for domestic and International orders. Our RF, microwave and millimeter wave products maintain a 99.4% availability and are part of the broadest selection in the industry.

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: 2 Way SMA Wilkinson Power Divider From 4 GHz to 8 GHz Rated at 10 Watts PE2080

URL: https://www.pasternack.com/2-way-sma-power-divider-4-8-ghz-10-watts-pe2080-p.aspx

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Pasternack reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Pasternack does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Pasternack does not assume any liability arising out of the use of any part or documentation.



PE2080

PE2080 CAD Drawing 2 Way SMA Wilkinson Power Divider From 4 GHz to 8 GHz Rated at 10 Watts

