

N Male to N Male Cable Using RG141 Coax



RF Cable Assemblies Technical Data Sheet

PE36589

Configuration

Connector 1: N MaleConnector 2: N MaleCable Type: RG141

Features

- Max Frequency 10 GHz
- PTFE (FG) Jacket

Applications

· General Purpose

· Laboratory Use

Description

Pasternack's PE36589 type N male to type N male cable using RG141 coax is part of our full line of RF components available for same-day shipping. Pasternack's flexible RF cable assemblies are ideal for applications where tight bends and flexure are required. This Pasternack type N to type N cable assembly has a male to male gender configuration with 50 ohm flexible RG141 coax. The PE36589 type N male to type N male cable assembly operates to 10 GHz.

Custom versions of most RF cable assemblies can be built and shipped same day. Custom cable assembly lengths can be obtained by specifying the desired length on the web site at time of order or by contacting a sales representative. Other available RF cable assembly value added services include connector orientation or clocking, heat shrink booting and custom labeling. RF testing can also be performed to document the electrical performance of your cable assembly.

Electrical Specifications

Minimum	Typical	Maximum	Units
DC		10	GHz
	29.4 [96.46]		pF/ft [pF/m]
		700	Vrms
		2,000	Vrms
		DC	DC 10 29.4 [96.46] 700

Specifications by Frequency

Description	F1	F2	F3	F4	F5	Units
Frequency	0.5	1	2.5	5	10	GHz
Insertion Loss (Typ.)	0.279	0.33	0.416	0.56	0.82	dB/ft
	0.92	1.08	1.36	1.84	2.69	dB/m

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: N Male to N Male Cable Using RG141 Coax PE36589

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 **Phone:** (866) 727-8376 or (949) 261-1920 • **Fax:** (949) 261-7451

Sales@Pasternack.com • Techsupport@Pasternack.com



N Male to N Male Cable Using RG141 Coax



RF Cable Assemblies Technical Data Sheet

PE36589

Mechanical Specifications

Cable Assembly

Weight 0.14 lbs [63.5 g]

Cable

Cable Type Impedance

Inner Conductor Type

Inner Conductor Material and Plating

Dielectric Type Number of Shields Shield Layer 1 Jacket Material Jacket Diameter RG141 50 Ohms Solid

Copper Clad Steel, Silver

PTFE

1

Silver Plated Copper PTFE (FG), Beige 0.19 in [4.83 mm]

Connectors

Description	Connector 1	Connector 2	
Туре	N Male	N Male	
Impedance	50 Ohms	50 Ohms	
Contact Material and Plating	Brass, Silver	Brass, Silver	
Dielectric Type	Teflon	Teflon	
Body Material and Plating	Brass, Nickel	Brass, Nickel	

Mechanical Specification Notes:

Compliance Certifications (see product page for current document)

Plotted and Other Data

Notes:

· Values at 25°C, sea level.

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: N Male to N Male Cable Using RG141 Coax PE36589

^{*}All cable assemblies have a length tolerance of 1.5% or \pm 3/8", whichever is greater.



N Male to N Male Cable Using RG141 Coax



RF Cable Assemblies Technical Data Sheet

PE36589

How to Order



Example: PE36589-12 = 12 inches long cable

PE36589-100cm = 100 cm long cable

N Male to N Male Cable Using RG141 Coax from Pasternack Enterprises has same day shipment for domestic and International orders. Our RF, microwave and millimeter wave products maintain a 99.4% availability and are part of the broadest selection in the industry.

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: N Male to N Male Cable Using RG141 Coax PE36589

URL: https://www.pasternack.com/n-male-n-male-rg141au-cable-assembly-pe36589-p.aspx

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Pasternack reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Pasternack does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Pasternack does not assume any liability arising out of the use of any part or documentation.

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 **Phone:** (866) 727-8376 or (949) 261-1920 • **Fax:** (949) 261-7451

PE36589 CAD Drawing N Male to N Male Cable Using RG141 Coax

