

TNC Male Right Angle to TNC Male Right Angle Cable Using RG400 Coax



RF Cable Assemblies Technical Data Sheet

PE3W00037

Configuration

Connector 1: TNC Male Right Angle
Connector 2: TNC Male Right Angle

Cable Type: RG400

Features

- Max Frequency 3 GHz
- 69.5% Phase Velocity
- · Double Shielded
- FEP Jacket

Applications

· General Purpose

Laboratory Use

Description

Pasternack's PE3W00037 TNC male right angle to TNC male right angle cable using RG400 coax is part of our full line of RF components available for same-day shipping. Pasternack's flexible RF cable assemblies are ideal for applications where tight bends and flexure are required. This Pasternack TNC to TNC cable assembly has a male to male gender configuration with 50 ohm flexible RG400 coax. The PE3W00037 TNC male to TNC male cable assembly operates to 3 GHz. The right angle TNC interfaces on the RG400 cable allow for easier connections in tight spaces. The double shielding of this Pasternack cable assembly provides excellent shielding effectiveness.

Custom versions of most RF cable assemblies can be built and shipped same day. Custom cable assembly lengths can be obtained by specifying the desired length on the web site at time of order or by contacting a sales representative. Other available RF cable assembly value added services include connector orientation or clocking, heat shrink booting and custom labeling. RF testing can also be performed to document the electrical performance of your cable assembly.

Electrical Specifications

Description	Minimum	Typical	Maximum	Units
Frequency Range	DC		3	GHz
VSWR			1.5:1	
Velocity of Propagation		69.5		%
Capacitance		32 [104.99]		pF/ft [pF/m]
Operating Voltage (AC)			500	Vrms

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: TNC Male Right Angle to TNC Male Right Angle Cable Using RG400 Coax PE3W00037

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 **Phone:** (866) 727-8376 or (949) 261-1920 • **Fax:** (949) 261-7451

Sales@Pasternack.com • Techsupport@Pasternack.com



TNC Male Right Angle to TNC Male Right Angle Cable Using RG400 Coax



RF Cable Assemblies Technical Data Sheet

PE3W00037

Specifications by Frequency

Description	F1	F2	F3	F4	F5	Units
Frequency	0.25	0.5	1	2.5	3	GHz
Insertion Loss (Max.)	0.05	0.07	0.1	0.2	0.23	dB/ft
	0.16	0.23	0.33	0.66	0.75	dB/m

Electrical Specification Notes:

Insertion Loss does not include the loss of connectors. Insertion Loss is estimated as 0.4dB of connector loss

Mechanical Specifications

Cable Assembly

Diameter 0.59 in [14.99 mm]

Cable

Cable Type Impedance Inner Conductor Type

Inner Conductor Material and Plating

Dielectric Type Number of Shields Shield Layer 1

Shield Layer 2 Jacket Material

Jacket Diameter

One Time Minimum Bend Radius

RG400 50 Ohms Stranded Copper, Silver

PTFE

Silver Plated Copper Braid Silver Plated Copper Braid

FEP, Tan

0.195 in [4.95 mm]

1 in [25.4 mm]

Connectors

Description	Connector 1	Connector 2		
Туре	TNC Male Right Angle	TNC Male Right Angle		
Specification	MIL-STD-348A	MIL-STD-348A		
Impedance	50 Ohms	50 Ohms		
Contact Material and Plating	et Material and Plating Brass, Gold			
Contact Plating Specification	30μ in. minimum	30μ in. minimum		
Dielectric Type	Teflon	Teflon		
Body Material and Plating	Brass, Nickel	Brass, Nickel		
Body Plating Specification	100μ in. minimum	100μ in. minimum		

Mechanical Specification Notes:

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: TNC Male Right Angle to TNC Male Right Angle Cable Using RG400 Coax PE3W00037

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 Phone: (866) 727-8376 or (949) 261-1920 • Fax: (949) 261-7451

Sales@Pasternack.com • Techsupport@Pasternack.com



TNC Male Right Angle to TNC Male Right Angle Cable Using RG400 Coax



RF Cable Assemblies Technical Data Sheet

PE3W00037

*All cable assemblies have a length tolerance of 1.5% or ± 3/8", whichever is greater.

Compliance Certifications (see product page for current document)

Plotted and Other Data

Notes:

How to Order

Part Number Configuration:

PE3W00037 - xx uu

Unit of Measure:
cm = Centimeters

Length
Base Number

Example: PE3W00037-12 = 12 inches long cable PE3W00037-100cm = 100 cm long cable

TNC Male Right Angle to TNC Male Right Angle Cable Using RG400 Coax from Pasternack Enterprises has same day shipment for domestic and International orders. Our RF, microwave and millimeter wave products maintain a 99.4% availability and are part of the broadest selection in the industry.

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: TNC Male Right Angle to TNC Male Right Angle Cable Using RG400 Coax PE3W00037

URL: https://www.pasternack.com/tnc-male-tnc-male-rg400u-cable-assembly-pe3w00037-p.aspx

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Pasternack reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Pasternack does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Pasternack does not assume any liability arising out of the use of any part or documentation.

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 **Phone:** (866) 727-8376 or (949) 261-1920 • **Fax:** (949) 261-7451

PE3W00037 CAD DrawingTNC Male Right Angle to TNC Male Right Angle Cable Using RG400 Coax

