

SMB Jack Connector Solder Attachment .062 inch End Launch PCB, .030 inch Diameter



RF Connectors Technical Data Sheet

PE44129

Configuration

- SMB Jack Connector
- 50 Ohms
- Straight Body Geometry

- .062 inch End Launch Interface Type
- Solder Attachment

Features

Gold Plated Contact

Applications

• General Purpose Test

PCB Applications

Description

Pasternack's PE44129 SMB jack connector with solder attachment for .062 inch end launch PCB is part of our full line of RF components available for same-day shipping.

Our SMB jack connector PE44129 datasheet specifications and drawing with dimensions are shown below in this PDF. Pasternack's broad catalog of RF, microwave and millimeter wave connectors allows designers to configure and customize their signal connections however they like. Whether the need is to provide an I/O for a board design, or simply create a custom cable assembly configuration, Pasternack has the right connector for the job. Pasternack can also expertly build your custom cable assemblies for you and ship same-day.

Mechanical Specifications

Size

 Length
 0.562 in [14.27 mm]

 Width/Dia.
 0.375 in [9.53 mm]

 Height
 0.312 in [7.92 mm]

 Weight
 0.004 lbs [1.81 g]

Material Specifications

Description		Material	Plating
Contact			Gold
Insulation		PTFE	
Body		Brass	Gold

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: SMB Jack Connector Solder Attachment .062 inch End Launch PCB, .030 inch Diameter PE44129

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 Phone: (866) 727-8376 or (949) 261-1920 • Fax: (949) 261-7451

Sales@Pasternack.com • Techsupport@Pasternack.com



SMB Jack Connector Solder Attachment .062 inch End Launch PCB, .030 inch Diameter



RF Connectors Technical Data Sheet

PE44129

Compliance Certifications (see product page for current document)

Plotted and Other Data

Notes:

SMB Jack Connector Solder Attachment .062 inch End Launch PCB, .030 inch Diameter from Pasternack Enterprises has same day shipment for domestic and International orders. Our RF, microwave and millimeter wave products maintain a 99% availability and are part of the broadest selection in the industry.

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: SMB Jack Connector Solder Attachment .062 inch End Launch PCB, .030 inch Diameter PE44129

URL: https://www.pasternack.com/smb-jack-standard-0.062-end-launch-connector-pe44129-p.aspx

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Pasternack reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Pasternack does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Pasternack does not assume any liability arising out of the use of any part or documentation.

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 **Phone:** (866) 727-8376 or (949) 261-1920 • **Fax:** (949) 261-7451

Sales@Pasternack.com • Techsupport@Pasternack.com

