

# SMB Jack Connector Solder Attachment .042 inch End Launch PCB, .020 inch x .010 inch Contact



## **RF Connectors Technical Data Sheet**

PE44137

# Configuration

- SMB Jack Connector
- MIL-STD-348A
- 50 Ohms

#### **Features**

- Max. Operating Frequency 4 GHz
- Good VSWR of 1.3:1

- Straight Body Geometry
- .042 inch End Launch Interface Type
- Solder Attachment
- Gold Plated Beryllium Copper Contact
- 30 µin minimum contact plating

# **Applications**

General Purpose Test

PCB Applications

#### **Description**

Pasternack's PE44137 SMB jack connector with solder attachment for .042 inch end launch PCB is part of our full line of RF components available for same-day shipping. Our SMB jack connector operates up to a maximum frequency of 4 GHz and offers good VSWR of 1.3:1.

Our SMB jack connector PE44137 datasheet specifications and drawing with dimensions are shown below in this PDF. Pasternack's broad catalog of RF, microwave and millimeter wave connectors allows designers to configure and customize their signal connections however they like. Whether the need is to provide an I/O for a board design, or simply create a custom cable assembly configuration, Pasternack has the right connector for the job. Pasternack can also expertly build your custom cable assemblies for you and ship same-day.

#### **Electrical Specifications**

Description	Minimum	Typical	Maximum	Units
Frequency Range	DC		4	GHz
VSWR			1.3:1	
Operating Voltage (AC)			335	Vrms

### **Mechanical Specifications**

#### Size

 Length
 0.562 in [14.27 mm]

 Width/Dia.
 0.375 in [9.53 mm]

 Height
 0.312 in [7.92 mm]

 Weight
 0.004 lbs [1.81 g]

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: SMB Jack Connector Solder Attachment .042 inch End Launch PCB, .020 inch x .010 inch Contact PE44137

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 **Phone:** (866) 727-8376 or (949) 261-1920 • **Fax:** (949) 261-7451

Sales@Pasternack.com • Techsupport@Pasternack.com



# SMB Jack Connector Solder Attachment .042 inch End Launch PCB, .020 inch x .010 inch Contact



## **RF Connectors Technical Data Sheet**

PE44137

#### **Material Specifications**

Description	Material	Plating
Contact	Beryllium Copper	Gold 30 µin minimum
Insulation	PTFE	
Body	Brass	Gold 3 µin minimum

#### **Environmental Specifications**

**Temperature** 

**Operating Range** 

-65 to +165 deg C

Compliance Certifications (see product page for current document)

#### **Plotted and Other Data**

Notes:

SMB Jack Connector Solder Attachment .042 inch End Launch PCB, .020 inch x .010 inch Contact from Pasternack Enterprises has same day shipment for domestic and International orders. Our RF, microwave and millimeter wave products maintain a 99% availability and are part of the broadest selection in the industry.

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: SMB Jack Connector Solder Attachment .042 inch End Launch PCB, .020 inch x .010 inch Contact PE44137

URL: https://www.pasternack.com/smb-jack-standard-0.042-end-launch-connector-pe44137-p.aspx

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Pasternack reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Pasternack does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Pasternack does not assume any liability arising out of the use of any part or documentation.

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 Phone: (866) 727-8376 or (949) 261-1920 • Fax: (949) 261-7451

Sales@Pasternack.com • Techsupport@Pasternack.com

# PE44137 CAD Drawing

SMB Jack Connector Solder Attachment .042 inch End Launch PCB, .020 inch x .010 inch Contact

