

6 dB Fixed Attenuator, 7/16 DIN Female To TNC Female Directional Rated To 50 Watts Up To 18 GHz



TECHNICAL DATA SHEET



6 dB Fixed Attenuator, 7/16 DIN Female To TNC Female Directional Rated To 50 Watts Up To 18 GHz												
Configuration												
Design	Fixed, Directional Attenuator											
Connector 1	7/16 DIN Female											
Connector 2	TNC Female											
Body Material and Plating	Aluminum Heatsink, Black Anodized											
body material and r fatting	Aluminum neatsink, black Albuizea											
Electrical Specifications												
Frequency Range, GHz	DC to 18											
Impedance, Ohms	50											
Attenuation Value, dB	6											
Maximum Input Power, Watts	50											
Maximum VSWR	1.6:1											
Frequency 1												
Range, GHz	DC to 6											
VSWR	1.3:1											
Attenuation Accuracy, dB	0.75											
Frequency 2												
Range, GHz	6 to 12.4											
VSWR	1.45:1											
Attenuation Accuracy, dB	0.75											
Frequency 3												
Range, GHz	12.4 to 18											
VSWR	1.6:1											
Attenuation Accuracy, dB	1											
Mechanical Specifications												
Temperature												
Operating Range, deg C	-55 to +125											
Size												
Length, in [mm]	4.01 [101.85]											
Width, in [mm]	3 [76.2]											
Height, in [mm]	3 [76.2]											
Weight, lbs [g]	1.796 [814.65]											

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: 6 dB Fixed Attenuator, 7/16 DIN Female To TNC Female Directional Rated To 50 Watts Up To 18 GHz PE7345-6

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Pasternack reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal.

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 **Phone:** (866) 727-8376 or (949) 261-1920 • **Fax:** (949) 261-7451 Sales@Pasternack.com • Techsupport@Pasternack.com



6 dB Fixed Attenuator, 7/16 DIN Female To TNC Female Directional Rated To 50 Watts Up To 18 GHz



PE7345-6

TECHNICAL DATA SHEET

Connector 1

Type Contact Material and Plating Hex Size, In. Body Material and Plating

Connector 2

Type Contact Material and Plating Outer Conductor Material and Plating Hex Size, In. Body Material and Plating

7/16 DIN Female Brass, Silver 11/16 Brass, Silver

TNC Female Beryllium Copper, Gold Stainless Steel, Passivated 11/16 Stainless Steel, Passivated

Compliance Certifications (visit www.Pasternack.com for current document) **RoHS** Compliant Yes

Plotted and Other Data

Notes:

Values at 25 °C, sea level **OUTPUT PORT HANDLES 5 WATTS MAX POWER** URL: http://www.pasternack.com/6db-fixed-7-16-female-tnc-female-50-watts-attenuator-pe7345-6-p.aspx

6 dB Fixed Attenuator, 7/16 DIN Female To TNC Female Directional Rated To 50 Watts Up To 18 GHz from Pasternack Enterprises has same day shipment for domestic and International orders. Our RF, microwave and fiber optic products maintain a 99% availability and are part of the broadest selection in the industry.

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Pasternack reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal.

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 Phone: (866) 727-8376 or (949) 261-1920 • Fax: (949) 261-7451 Sales@Pasternack.com • Techsupport@Pasternack.com

PE7345-6 CAD Drawing 6 dB Fixed Attenuator, 7/16 DIN Female To TNC Female Directional Rated To 50 Watts Up To 18 GHz

																		00	, uc		u i				<u> </u>	50	••	a	13			U											
tion	Output Connector	7/16 Male	7/16 Male	7/16 Female	7/16 Famale	7/16 Famale	7/16 Female	N Male	N Male	N Male	N Male	N Female	N Female	N Female	N Female	N Female	N Female	N Female	SMA Male	SMA Male	SMA Male	SMA Female	SMA Female	SMA Female	SMA Female	SMA Female	SMA Female	SMA Female	TNC Male	TNC Male	TNC Male	TNC Male	TNC Female	TNC Female	TNC Female	TNC Famale	TNC Female	TNC Female	TNC Female			E AT ANY TIME.	A 2233
configurat				2											_							S	S	S	S	0	000	0 0.	,	-			-							tion Level		NOMINAL.	SIZE A
Part Number Configuration	Input Connector	7/16 Female	N Female	7/16 Male	7/16 Female	N Male	N Female	7/16 Female	N Female	SMA Female	TNC Female	7/16 Male	7/16 Female	N Male	N Female	SMA Male	TNC Male	TNC Female	7/16 Female	N Female	TNC Female	7/16 Male	7/16 Female	N Male	N Female	SMA Male	SMA Female	TNC Female	7/16 Female	N Female	SMA Female	TNC Female	7/16 Male	7/16 Female	N Male	SMA Male	SMA Female	TNC Male	TNC Female	Indicates Attenuation Level		NOTES: 1. UNLESC OTHERWISE SPECIFIED ALL DIMENSIONS ARE NOMINAL. 2. UNLESECIFICATIONS ARE SUBJECT TO CHANGE WITHOUT NOTICE AT ANY TIME. 3. DIMENSIONS ARE IN INCHES [mm].	SCALE N/A
	××	10	11	12	13	14	15	16	17	18	19	20	21	22	23	25	26	27	28	29	3 5	32	33	34	35	36	37	99	40	41	42	43	44	45	46	48	49	50	51	Ń-		SIFIED AL SUBJEC ES [mm].	
formation	DIM "A" (REF.)	0.68	0.54		N GR	0.04	5.5	0.95	0.98		1.12	1.16																														OTHERWISE SPEC CIFICATIONS ARE IONS ARE IN INCHE	FILE 102512
Table of Information	Connector Type	SMA Male	SMA Female		TNC Male	TNC Female		N Female	N Male		7/16 Male	7/16 Female													2B	0 4 0 0 4 0	ר - - גי	2														NOTES: 1. UNLESS 2. ALL SPE 3. DIMENSI	CAD FILE
" ~ "		S	S					2	_		2	2								0.25		[2.2]			8X 4-40 UNC	TAP X 250 [6 4]	DP ROTH SIDE			-					- 241					-	ŝ	ристп∟е РЕ73xx-yy	FSCM NO. 53919
" _۸ " 3.22	A [81.8]	1																		0.70			IOP VIEW				[+.0.]			•											⊕	Pasternack Enterprises, Inc. P.O. Box 16759 Irvine CA 92623	Phone: (949) 261-1920 Fax: (949) 261-7451 Website: www.pasternack.com E-Mail: sales@pasternack.com